



FCE® maximal



FCE® maximal

FTE maximal
Mogoda, 110 - Pol. Ind. Can Salvatella
08210 Barberà del Vallès (Barcelona)
Tel. +34 93 729 27 00
Fax +34 93 729 30 73
www.ftemaximal.com
ftemaximal@ftemaximal.com

Antenas exteriores
Outdoor antenna
Antennes Extérieures
Antenne Esterne
Terrestrische Antennen
Antenas exteriores

F 0-F / FM 3-F





F 0-F



F 0-F

Código Code Code	9002005-F	Codice Code BN
Nº de elementos Elements Nb Éléments	1 Omnidireccional 1 omnidirectional 1 omnidirectionnel	Nº di elementi Elements Anzahl der Elemente
Banda Band Bande	FM (87,5-108 MHz)	Banda Band Band
Ganancia (dB) Gain (dB) Gain (dB)	1	Guadagno (dB) Gain (dB) Gewinn (dB)
Relación delante/atrás (dB) Front to Back ratio (dB) Rapport avant / arrière (dB)	0	Rapporto fronte / retro (dB) Front to Back ratio (dB) Vor- / Rückverhältnis (dB)
Ángulo de recepción Horizontal (-3 dB) Half power beam width Horiz. (-3 dB) Angle de réception horizontale (-3 dB)	360°	Angolo di ricezione orizzontale (-3 dB) Half power beam width Horiz. (-3 dB) Öffnungswinkel (-3 dB)
Impedancia (Ω) Impedance (Ω) Impédance (Ω)	75	Impedenza (Ω) Impedance (Ω) Impedanz (Ω)
Longitud (mm) Length (mm) Longueur (mm)	800	Lunghezza (mm) Length (mm) Länge (mm)

FM 3-F



FM 3-F

Código Code Code	9002025-F	Codice Code BN
Nº de elementos Elements Nb Éléments	3	Nº di elementi Elements Anzahl der Elemente
Banda Band Bande	FM	Banda Band Band
Ganancia (dB) Gain (dB) Gain (dB)	6	Guadagno (dB) Gain (dB) Gewinn (dB)
Relación delante/atrás (dB) Front to Back ratio (dB) Rapport avant / arrière (dB)	18	Rapporto fronte / retro (dB) Front to Back ratio (dB) Vor- / Rückverhältnis (dB)
Ángulo de recepción horizontal (-3 dB) Half power beam width Horiz. (-3 dB) Angle de réception horizontale (-3 dB)	68°	Angolo di ricezione orizzontale (-3 dB) Half power beam width Horiz. (-3 dB) Öffnungswinkel (-3 dB)
Impedancia (Ω) Impedance (Ω) Impédance (Ω)	75	Impedenza (Ω) Impedance (Ω) Impedanz (Ω)
Longitud (mm) Length (mm) Longueur (mm)	1150	Lunghezza (mm) Length (mm) Länge (mm)